



MOSLEY MODEL MINI-32-A



"Thank you for a fine antenna and also for the accuracy of the claims in your ad, I was amazed." **KK2J**

The MINI-32-A is built in the Mosley tradition of quality, simplicity, and strength.

- 2 Elements on 10, 15, 20
- Ultra Light Weight
- Small Foot Print
- Good all-around performance
- Stainless Steel Hardware
- 2 Year Warranty

UPGRADE YOUR MINI-32-A!

Add 12 & 17 meters with the MINI-WARC Kit. See [Conversion Kits](#) for more details.

Frequency, MHz	28, 21, 14	
Power Rating, watts CW	500	
Power Rating, watts SSB	1000	
Power Rating, AM/FM	250	
Power Rating, RTTY/AMTOR	250	
VSWR at frequency	1.0/1 to 2.0/1	
Forward Gain, dBd 10 meters	5.1	
Forward Gain, dBd 15 meters	4.5	
Forward Gain, dBd 20 meters	3.3	
Front-to-Back Ratio, dB 10 meters	17 (avg.)	
Front-to-Back Ratio, dB 15 meters	17 (avg.)	
Front-to-Back Ratio, dB 20 meters	17 (avg.)	
Boom Length	6 ft	1.83 m
Maximum Element Length	19.6875 ft	6 m
Turning Radius	10.29 ft	3.14 m
Mast Size hardware (equipped)	1.5 in	3.81 cm
Assembled weight	9.5 lbs	4.31 kg
Wind Surface Area	2.5 sq ft	0.232 sq m
Wind Load, EIA Standard 80 MPH	38 lbs	17.24 kg
Warranty	2	
Recommended Coax	Belden RG-8 / RG-213	
Options (E-mail for details.)	Add 12 & 17 Meters	

Standard MINI-32-A next to a cut down MINI-32-ASP. Box is only 47 inches long!
[E-mail](#) for details.



The Mosley MINI-32-A is the answer to the antenna space problem, while giving you great performance and durability.

